

Celadon Inc.
RCV-5000 IR to RS-232 Output Table
Device: QuadScan Elite

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol
 Infrared Code Format: NEC - Device ID: 7B02
 Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description
 Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver
 RCV-5000 Data File: quadsn1_r.hex
 Data: 9600 baud, 8, Odd, 1, HEX OUTPUT
 TD Pin 2, RD Pin 3
 Note: String requires carriage return at end = 0DH

Command	Pronto Button	RCV-5000 Output
Input Aspect - 4:3	0	10 01 0D
Input Aspect - 4:3LBox	1	10 02 0D
Input Aspect - 16:9	2	10 03 0D
Input Source Select - Auto	3	07 01 0D
Input Source Select - VGA Pass	4	07 02 0D
Input Source Select - YUV A	5	07 03 0D
Input Source Select - YUV B	6	07 04 0D
Input Source Select - S-VHS A	7	07 05 0D
Input Source Select - S-VHS B	8	07 06 0D
Input Source Select - Composite A	9	07 07 0D
Input Source Select - Composite B	10	07 08 0D
Output Resolution - D-ILA	11	0B 01 0D
Output Resolution - Triple	12	0B 02 0D
Output Resolution - Quadrupled	13	0B 03 0D
Output Resolution - XGA	14	0B 04 0D
Output Resolution - SVGA	15	0B 05 0D
Output Resolution - Doubled	16	0B 06 0D
Output Resolution - VGA	17	0B 07 0D
Output Aspect - 4:3 Top	18	1A 01 0D
Output Aspect - 4:3 Middle	19	1A 02 0D
Output Aspect - 4:3 Bottom	20	1A 03 0D
Output Aspect - 16:9 Top	21	1A 04 0D
Output Aspect - 16:9 Middle	22	1A 05 0D
Output Aspect - 16:9 Bottom	23	1A 06 0D

Celadon, Inc.
 50 Mitchell Blvd.
 San Rafael, CA 94903
 Sales: (707) 648-1098
 Main Tel: (415) 472-1177
 Main Fax: (415) 472-1179
 sales@celadon.com