

Celadon Inc.
RCV-5000 IR to RS-232 Output Table
Device: NEC 84VP4 (four 42VP4 Plasma)

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol
 Infrared Code Format: NEC - Device ID: 7B02
 Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description
 Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver
 RCV-5000 Data File: nect841_r.hex
 Data: 9600 Baud, 8, O, 1, HEX Output
 Standard Transmit and Receive pinout

NEC Command	Pronto Button	RCV-5000 Output
Power ON	0	9F 80 60 4E 00 0CD
Power OFF	1	9F 80 60 4F 00 0CE
Input (Video 1)	2	DF 80 60 47 01 01 08
Input (Video 2)	3	DF 80 60 47 01 02 09
Input (Video 3)	4	DF 80 60 47 01 03 0A
Input (HD1)	5	DF 80 60 47 01 05 0C
Input (HD2)	6	DF 80 60 47 01 06 0D
Input (RGB1)	7	DF 80 60 47 01 07 0E
Screen Mode Stadium	8	DF 80 60 51 01 02 13
Screen Mode Zoom	9	DF 80 60 51 01 03 14
Screen Mode Normal	10	DF 80 60 51 01 04 15
Screen Mode Full	11	DF 80 60 51 01 05 16
Single Mode TV1 (UL)	12	DF 80 60 03 03 01 01 01 0C8
Single Mode TV2 (UR)	13	DF 80 60 03 03 01 02 01 0C9
Single Mode TV3 (LR)	14	DF 80 60 03 03 01 03 01 0CA
Single Mode TV4 (LL)	15	DF 80 60 03 03 01 04 01 0CB
Multi Mode (4 Screens) TV1 (UL)	16	DF 80 60 03 03 03 01 01 0CA
Multi Mode (4 Screens) TV2 (UR)	17	DF 80 60 03 03 03 02 01 0CB
Multi Mode (4 Screens) TV3 (LR)	18	DF 80 60 03 03 03 03 01 0CC
Multi Mode (4 Screens) TV4 (LL)	19	DF 80 60 03 03 03 04 01 0CD

Celadon, Inc.
 50 Mitchell Blvd.
 San Rafael, CA 94903
 Sales: (707) 648-1098
 Main Tel: (415) 472-1177
 Main Fax: (415) 472-1179
 sales@celadon.com